

Interpret the Interface Log

The 2 time fields (**Time the Web Services were invoked** and **LRS Time given to the web services**) should always have the same value and correlate to the time the interface run was initiated. That value is the **LRS Time** given to the Roads & Highways web services for that run.

The times given to the web services for **Last Invoked Time** and **Last LRS Time** will have the same value and be the time from the closest previous log entry with a Status of **COMPLETE**. That way the interface instructs the web services to give the changes from the last run to the current run.

The Status field can have the following values:

- **COMPLETE** – The full mode interface ran successfully and is complete.
- **RH_INTERFACE_COMPLETE** – The test mode interface ran successfully and is complete.
- **EXPORT_NETWORK_COMPLETE** – The Export Network web service was called successfully but the interface did not complete. See [Troubleshooting Interface Runs](#) for help with this.
- **ERROR** – The interface did not complete successfully. See [Troubleshooting Interface Runs](#) for help with this.

The Comments field is not populated by the interface and can be used by the user to add any information they want to attach to a given interface run.